## FIREANGE SPECIFICATION

## FS1524W2-T WIRELESS ALARM CONTROL UNIT

Battery type	10 year sealed for life lithium
	Smart RF - works with any Smart RF ready device
	<ul> <li>Features Smart RF technology - Wirelessly interlink up to 50 FireAngel Smart RF products, including FireAngel Connect Gateway</li> </ul>
TEST/ 4(X	Connects to FireAngel Connect Gateway
	Smart RF - when one alarm sounds, they all sound
	Separate fire and CO alarm identifications
	A remote interface for up to 50 Smart RF devices
	<ul> <li>Test function - allows you to test all interlinked alarms from one - testing alarms becomes simple and fast</li> </ul>
Free Angel assessments	<ul> <li>Silence function - silence all interlinked smoke and heat alarms An alarm cannot be silenced if CO has been detected, however the locate function allows the initiating CO alarm to be located</li> </ul>
WHELESS A AGM CONTROL UNIT MININE WHEN ON HAN AND AN THE THT ASSIST: COMENTANCE	<ul> <li>Locate function - silence all wirelessly interlinked alarms except the initiating alarm</li> </ul>
	<ul> <li>Memory function - if one of the alarm indicators is flashing every 10 seconds a smoke, heat or CO alarm has been activated</li> </ul>
	<ul> <li>Increases accessibility for individuals who are unable to easily test or access alarms e.g vulnerable adults, disabled, individuals living in properties with high ceilings</li> </ul>
Technical Specification	n

## lechnical Specification

Product Dimensions	90mm (width) x 90mm (height) x 22.5mm (depth)
Supply voltage	3VDC
Battery	10 year sealed lithium
Installation positions	Wall / Portable
Technology	Smart RF
Operating temperature	+4°C to +38°C
Operating humidity	Up to 90% RH non-condensing
Storage temperature	-20°C to +60°C
Storage humidity	Up to 93% RH non-condensing
Plastic material	ABS, UL94 VO fire retardant
Warranty	5 years
Weight	142g
Independently tested to	ETSI EN 300 220-2 V2.4.1, ETSI EN 301 489-1 V1.9.2, ETSI EN 301 489-3 V1.6.1
Maximum number of connected units	50 Smart RF devices
Operating Frequency	868 MHz
Range	35m (over 200m in clear air)
Master pack quantity	10



Create a Safety Network

Add a Smart RF Radio Module to wirelessly interlink up to 50 Smart RF devices with a simple 2 step process.









For further information or sales enquiries, contact your local Specification Manager: www.fireangel.co.uk/specification-manager