

CW1-PF-T MAINS POWERED CARBON MONOXIDE ALARM + PUSH FIT BASE

Sensor type	Electrochemical
Battery type	Mains powered with 9V battery back-up

The CW1-PF is a mains powered carbon monoxide alarm with high performance electrochemical sensor, 9V zinc carbon battery back-up and an improved PUSH-FIT base for quicker and easier installations; designed to ensure quick and easy installation of base unit to the mains feed supply at installation stage (1st fix) and for quicker and easier connection of alarm to base unit (2nd fix). Providing early warning of the presence of CO in the home through alarm and LED display.



- 230V mains powered carbon monoxide alarm
- 9V battery back-up
- Improved PUSH-FIT base for quicker installations
- Electrochemical sensing technology
- Large central test button makes weekly testing easy
- LED operating indicators - Power, Fault, Alarm
- Low battery warning indicator
- Multi-alarm interconnect up to 12 smoke (SW1-PF), heat (HW1-PF) & CO (CW1-PF) units – when one sounds they all sound
- Safety clip feature, to prevent installation of smoke alarm without battery installed
- 5 year warranty
- EN 50291-1: 2010

Technical Specification

Dimensions	126mm (diameter) x 49mm (depth)
Model number	CW1-PF-T
Description	230V CO with zinc carbon battery back-up
Technology	Electrochemical
Alarm sound level	85db at 3 metres
Battery type	9V PP3 zinc carbon
Operation AC/DC	AC
Installation positions	Ceiling
Operating temperature	0°C (32°F) and 40°C (104°F).
Operating humidity	TBC
Storage temperature	TBC
Storage humidity	TBC
Warranty	5 years
Approvals	EN 50291-1: 2010